

PRODUCT DESCRIPTION

The PM 1A is a mic preamp/DI in the Modular Series. It is based on a classic TUBE-TECH design, improved to provide even higher fidelity and some new features: An impedance switch to match the input perfectly to all microphone types, an overload indicator and 2 dB gain steps.

Serious listening tests of the PM 1A have revealed a sound

quality second to none, placing it among a handful of the world's very best designs.

The PM 1A DI continues the TUBE-TECH tradition of extremely good sounding DI's, delivering world class sound for a.o. bass and guitar recordings.

You simply won't find a better DI than this!



FEATURES

- All-tube design featuring push-pull output amplifier
- Frequency response @ -3 dB: 5 Hz to 60 kHz
- Typical noise: 5 dB @ 200Ω
- CMRR: > 60 dB @ 10 kHz
- Gain: +10 dB to +70 dB in 2 dB steps - DI gain: 0-60 dB
- Selectable mic input impedance: 600 Ω/1.2 kΩ/2.4 kΩ
- Selectable pad in front of input transformer (-20 dB)
- Selectable +48 V phantom power
- Low cut filter (20 Hz/40 Hz/Off)
- Phase reverse
- Overload indicator
- Gold plated switches
- DI Jack input for a variety of instruments
- DI input impedance > 1 MΩ
- MU-metal shielded input transformer
- In- and output are transformer balanced and fully floating